



Eltako

30 999 003 - 1, 30 999 005 - 1

Radio pushbutton inserts FTE215 and FTE215BLE

Temperature at mounting location:
-20°C up to +50°C.
Storage temperature: -25°C up to +70°C.
Relative humidity:
annual average value <75%.

Radio pushbutton inserts with EnOcean energy generator for other brands.

Generates the power for wireless telegrams itself when the button is pressed, therefore there is no connecting wire and no standby loss.

The scope of supply comprises the mounting base and the attachment frame for FT55 with mounted PTM215 (with encryption) EnOcean radio module, or PTM215B (Bluetooth).

Wireless pushbuttons with one rocker can transmit two evaluable signals, wireless pushbuttons with double rocker can transmit four evaluable signals.

The mounting base can be screwed onto a flat surface or glued to the wall, on glass or on furniture using the enclosed adhesive foil. Use the sleeves in the 55 mm socket box for screw mounting.

Before screwing, remove the attachment frame comprising the wireless module from the mounting base. To do this, press the latches on the mounting base outwards. Then screw or glue the mounting base - with the latches at top and bottom - snap on the frame with the attachment frame and snap on the attachment frame comprising the wireless module - with the marking 0 on the back always pointing to the top.

We recommend stainless-steel counter-sunk 2.9x25 mm, DIN 7982 C, for screw connections. Both with rawl plugs 5x25 mm and with 55 mm switch boxes.

Usability with the frames following manufacturers:

manufacturers	Designation
Berker	S1, B1
Gira	Standard 55, E2, Event
Hager	Kallysto Pur
Jung	A500, AS500, A Plus
Merten	Smart M, M-Pure, M-Plan
OPUS	InForm, Fusion
Schneider	Single frames

FTE215:

The wireless module PTM215 can be taught-in encrypted in all tap-radio actuators from the series 61, 62 and 71, and also in the FAM14 compatible with the encryption

FTE215BLE:

The wireless module PTM215B inside the pushbutton kann be taught-in in Bluetooth devices. Bluetooth Low Energy works with 2,4 GHz frequency.

The radio telegrams are encrypted with AES-128 (CBC). The wireless module PTM215B has an NFC interface according to ISO 14443.

Teaching-in wireless sensors in wireless actuators

All sensors must be taught-in in the actuators so that they can detect and execute commands.

The teaching-in procedure is written in the actuator manual.

Manuals and Documents in further Languages



http://eltako.com/redirect/FTE215_FTE215BLE



enocean®
DER EINZIGARTIGE PROFESSIONAL
SMART HOME FUNK-STANDARD

FTE215

Frequency	868.3 MHz
Transmit power	max. 10 mW

FTE215BLE

Frequency	2402 - 2480 MHz
Transmit power	max. 1 mW

Hereby, Eltako GmbH declares that the radio equipment type FTE215 and FTE215BLE is in compliance with Directive 2014/53/EU.

The full text of the EU declaration of conformity is available at the following internet address: eltako.com

Must be kept for later use!

Eltako GmbH

D-70736 Fellbach

Technical Support English:

+49 711 943 500 25

technical-support@eltako.de

eltako.com