Command Elite COMD1

DALI addressable luminaire integrated detector





Overview


- A compact luminaire based addressable sensor that utilises a passive infra-red detector (PIR), a photocell and an infra-red receiver for use with the infra-red handset (supplied separately).
- Integrated detector
- Regulating photocell ensures minimum maintained light level taking into account the contribution from adjacent luminaires
- Presence detection
- Control using hand held remote (COMDSSC)
- DALI consumption 10mA
- Mode selector with LED feedback
- Clip on fascias

Order codes

COMD1 DALI Addressable PIR Luminaire Integrated Detector

Product is supplied within a luminaire and not individually. To specify this product within a luminaire please consult our Technical Support team

Dimensions



VERSION	L	W	Н
Cut out 56.5mm x 26mm	58	29	22